



**Weatherford®**

# WellPilot™ Variable Speed Drive for Rod Pumping



Continuous pump fill control with speed and torque override for optimum management of rod pumped wells.

# WellPilot Variable Speed Drive for Rod Pumping

## Features

- Minimizes mechanical stress on equipment
- Reduces power consumption
- Minimizes equipment wear
- Maximum torque from zero to base speed
- High speed operation up to 120 Hz
- Controls low fluid level without pumpoff
- Reduce or eliminate rod pound
- Maximizes run times
- Flexible configuration
- Simple operation and setup
- Programmable restart function
- Package designed for all environmental conditions

The critical challenge in rod pumped wells is to match the pumping speed to the varying production capacity of the well while protecting the system from mechanical damage. Conventional rod pump controllers (RPCs) are very effective in controlling the fluid level by cycling the well on and off based on available fluid. In some cases, this is not the best method of optimization because a well may be off too long resulting in inefficient operations or causing pumps to stick due to sand content.

What is needed in the market today is a control system that can infinitely vary the speed while controlling polished rod torque throughout the speed range.

Weatherford meets this need with the *WellPilot* controller providing continuous pump fill control with speed and torque override for optimum management of rod pumped wells.

Weatherford's *WellPilot* controller uses an integral RPC in conjunction with precision speed and torque control to ensure that the well pumps only as fast as required. This not only allows you to match the pumping speed to well conditions, but also supplies the required torque to operate when fully loaded. Precision torque control also means there is no need to oversize the drive relative to the motor for pump startup

Drive reliability requires the proper enclosure to protect the sensitive electronics from foreign material as well as extreme temperature variations. The *WellPilot* controller uses an engineered package with through-hole mounting of the amplifier heat sink to reduce the heat and the overall size requirement of the cabinet.

Our NEMA Type 3R enclosure layout provides additional room for optional internal components while mechanical interlock enhances the safety of the package.

## Interfaces

- Graphic keypad/display
- Serial communications—local/remote
- Portable keypad interface

## Cost Savings

- Continuous operation eliminates inrush current and stuck pumps
- Adjustable pump fillage setpoints reduce rod pound



# WellPilot Variable Speed Drive for Rod Pumping

## Performance

- Adjustable speed eliminates need for sheave changes
- Auto restart after power loss or fault condition
- Overvoltage suppression software that eliminates the need for dynamic braking in most applications
- Auto learn function that allows the controller to find the wells optimum speed settings
- Auto speed control can adjust the pumping speed every stroke based on pump fillage
- Low speed detection
- Simple setup decreases startup time
- Reliable operation
- Configurable menu allows easy access to critical information
- Graphic dynamometer display
- Built-in communication module
- Direct measurement of load and position for accurate determination of fluid level
- Inferred production algorithm for total fluid measurement with 30 day historical data storage
- Remote ESD functionality

## Dimensional Data

Encl. Size	HP	Height		Width		Depth		Weight	
		in.	cm.	in.	cm.	in.	cm.	lbs.	kg.
1	5-30	36	91.44	24	60.96	18	45.72	200	90.72
2	40-50	48	121.92	24	60.96	18	45.72	240	108.86
3	60-100	48	121.92	30	76.2	18	45.72	280	127.0
4	125-150	60	152.4	36	91.44	20	50.8	350	158.76

### Data Protection

- Drive keypad can archive and store the critical drive parameters in the event you need to transfer the information to another drive or reload the values
- PC interface software allows you to transfer critical drive parameters to PC for storage and reference
- Multilevel password protection allows critical drive parameters to be accessible only with a password

### Drive Protection

- Ground fault
- Motor phase-to-phase short circuit
- AC input overvoltage
- AC input undervoltage
- Instantaneous overcurrent
- Motor overload
- Heat sink over temperature
- Power transistor fault
- Logic power undervoltage
- Inlet and outlet phase loss protection
- Motor runaway
- Memory malfunction
- Processor running fault

# WellPilot Variable Speed Drive for Rod Pumping



## Specifications

<b>Electrical</b>	
<b>Input Supply</b>	
Three-phase voltage	230, 380, 480 Vac ( $\pm 10\%$ )
Three-phase frequency	50 to 60 Hz ( $\pm 5\%$ )
Single-phase voltage	230, 480 Vac ( $\pm 10\%$ )
Single-phase frequency	50 to 60 Hz ( $\pm 5\%$ )
<b>Power Factor</b>	
Overall	1.00 displacement power factor 0.94 overall power factor at all speeds
<b>Output Rating</b>	
Voltage	Zero to input voltage, three-phase
Frequency	Zero to 120 Hz flux vector control Zero to 300 Hz variable frequency control
Switching frequency	Programmable, 2 to 8 kHz varies with Hp
Overload current	110 to 120% of rated for one minute (normal duty)
<b>Conversion</b>	
Rectifier unit	Six-diode, three-phase (six-pulse) full wave bridge below 40 Hp Diode-SCR, 6-phase (12-pulse) full-wave bridge for 40 Hp and above
Inverter unit	Six-IGBT, four-quadrant, trap or sine wave output
<b>Environmental</b>	
Operating temperature ( $^{\circ}\text{F}/^{\circ}\text{C}$ )	-40 to 122 (-40 to 40)
Storage temperature ( $^{\circ}\text{F}/^{\circ}\text{C}$ )	-4 to 140 (-20 to 60)
Relative humidity	5% to 95%, noncondensing
Altitude	Zero to 3300 ft. (1000 m) at full rating
<b>Inputs and Outputs</b>	
Analog inputs	Six 12-bit analog inputs: 0 to 5 Vdc, 1 to 5 Vdc, or 4 to 20 mA
Analog outputs	Two 12-bit analog outputs (4 to 20 mA)
Pulse output	0 to 32 kHz
Digital inputs	Eight
Digital outputs	Eight
Serial Communications	
Modbus <sup>®</sup> port	8500 protocol EIA RS232 and RS422/485, 1200 to 19200 baud Modbus ASCII, Modbus RTU
<b>Enclosure</b>	
UL listed package	Type 3R Engineered for all weather conditions Door interlocked breaker main disconnect Front mounted keypad and controls in secondary door Control transformer Panel mount enclosure (sizes one to three) Floor mount enclosure (size four)
<b>Optional</b>	
	24 Vdc power supply for external analog signals Communication (Ethernet) Line/load reactors IEEE-519 rated inlet harmonic package Long lead filter (DV/DT)



**Weatherford<sup>®</sup>**

515 Post Oak Blvd.  
Suite 600  
Houston, Texas 77027 USA  
Tel: 281.348.1000  
info@ep-weatherford.com  
ep-weatherford.com

Weatherford products and services are subject to the Company's standard terms and conditions, available on request or at weatherford.com. For more information contact an authorized Weatherford representative. Unless noted otherwise, trademarks and service marks herein are the property of Weatherford. Specifications are subject to change without notice. Weatherford sells its products and services in accordance with the terms and conditions set forth in the applicable contract between Weatherford and the client.